

VX-3000DS POWER SUPPLY MANAGER

The VX-3000DS is an Emergency Power Supply Manager used for the SX-2000, VX-2000 and VM-3000 systems. It is a 3U rack-mount unit equipped with a battery charger and dual switching power supplies, which contribute to rack space, energy-saving and lightweight design. The VX-3000DS features easy maintenance as function setting switch and shutdown switch inside the front panel, and fuse replacement can be performed on the unit's rear side.

AG FOWER BUTTEN AMAGES AN 20000S

Article number: VX-3000DS CE Alternative products: VX-3150DS



VX-3000DS POWER SUPPLY MANAGER

Specifications

Power source	220 - 230 V AC, 50 / 60 Hz
Power consumption	2800 W max.(at rated output with charging),350 W (EN 60065)
Outputs	DC power output: 8 x 31 V (19 – 33 V) 25 A max. each, M4 screw terminal, distance between barriers: 11 mm 3 x 31 V (19 – 33 V) 5 A max. each, removable terminal block (3 x 2 pins) 1 x 24 V (16 – 25 V) 0.3 A max., removable terminal block (1 x 2 pins
Charging method	Temperature compensated trickle charging
Charging output voltage	27.3 V ±0.3 V (at 25 °C), Temperature correction coefficient: -40 mV/ °C
Battery connection	One each positive and negative terminal, applicable cable diameter: AWG 6 – AWG 0 (AWG 1/0) (16 mm2 – 50 mm2)Line resistance within 4 mΩ / total
Control connector	RJ45 female connector for connecting the system and cascade connectionShielded Twisted-pair straight cable (TIA/EIA-568A standard)
DS LINK IN/OUT	Type of control signal: Battery check, AC power status, DC power status, charging circuit failure, battery failure, and communication
Panel indicator	AC power IN 1, IN 2 (Green), Charging (Green), Battery power (Green), Battery connect (Green), Battery condition (Green)
Operating humidity	90 % RH or less (no condensation)
Operating temperature	-5 °C to +45 °C
Certificates	EN 54-4
Dimensions	482 x 132.6 x 400.5 mm (W x H x D)
Gross weight	15,49 KG
Finish	Steel plate, surface-treated, 30% gloss, paint, black,
Weight	11.8 kg



VX-3000DS POWER SUPPLY MANAGER

Appearance

