FONESTAR

FS-3000RGUB



Player and mixer in one device, with mic. and aux input, USB/SD/MP3 player/recorder, digital FM tuner and bluetooth receiver.

RESPONSE	20-20,000 Hz
CONTROLS	GND lift earth disconnection
INPUTS	1 balanced mic. combo (XLR and 6.3 mm jack) 1 stereo audio, 2 x RCA and 3.5 mm jack 3 aux, 2 x RCA 1 tape in, 2 x RCA
OUTPUTS	1 balanced stereo audio, 2 x XLR 2 stereo audio, 2 x RCA 1 tape out, 2 x RCA 1 stereo headphones, 6.3 mm jack
POWER SUPPLY	230/115 V AC, 50 W
DIMENSIONS	430 x 44.5 x 150 mm depth. 1 U 19' rack
WEIGHT	1.5 kg
ACCESSORIES	2 connection cables 2 x RCA Mounts for 19' rack assembly AM and FM aerial

© 2018 Copyright by FONESTAR SISTEMAS, S.A.

www.fonestar.com Página: 1/1